

DJ Controller

DDJ-SZ2



Firmware Update Guide

A. Checking the current firmware version of DDJ-SZ2

1. Connect your DDJ-SZ2 to your computer using a USB cable.

2. Launch the Settings Utility.

• For Mac:

1. In Finder, open the [Applications] folder.
2. Click [Pioneer] > [DDJ-SZ2] > [DDJ-SZ2 Settings Utility].

• For Windows 10:

In the Windows [Start] menu, click [Pioneer] > [DDJ-SZ2] > [DDJ-SZ2 Settings Utility].

• For Windows 8.1:


In [Apps view], click [Pioneer] > [DDJ-SZ2] > [DDJ-SZ2 Settings Utility].

• For Windows 7:

In the Windows [Start] menu, click [All Programs] > [Pioneer] > [DDJ-SZ2] > [DDJ-SZ2 Settings Utility].

3. Check the Firmware Version in the Settings Utility

The firmware version is displayed in the [About] tab.



B. Checking the downloaded file

1. Unzip the downloaded file.

- For Mac:
Save the downloaded file [DDJ-SZ2_vxxx_Mac.zip] to an arbitrary folder such as desk top and unzip it.
The [DDJ-SZ2_vxxx_MAC.dmg] file is generated when the file is unzipped and then double click to mount it.
- For Windows:
Save the downloaded file [DDJ-SZ2_vxxx_Win.zip] to an arbitrary folder such as desk top and unzip it.

2. Check the unzipped file.

- For Mac:
The [DDJ-SZ2_vxxx_MAC] folder is generated when the file is extracted.
Please ensure the following files are included in the folder.
[DDJ-SZ2_vxxx.app]
- For Windows:
The [DDJ-SZ2_vxxx_WIN] folder is generated when the file is unzipped.
Please ensure the following files are included in the folder.
[DDJ-SZ2_vxxx.exe]

- ✓ **xxx** is numerical characters of the new firmware version.
- ✓ Depending on your computer settings, the extension such as .exe or .app may not be displayed.

C. Preparing for the update

1. Connect the DDJ-SZ2 to computer.

Connect your DDJ-SZ2 to your computer using a USB cable.

(Connect the USB cable to USB-A terminal.)

2. Activate the update mode.

Press the power button while pressing the [SHIFT] button and the [SYNC] buttons on the left deck.

Once the update mode is activated, the LED at the top of the MASTER level meter flashes.



D. Updating the firmware through a computer

1. Updating procedures


Before updating, close all the applications running on the computer.

<STEP1> Open the update program.

- For Windows:
Double click [DDJ-SZ2_vxxx.exe] to open the file.
- For Mac:
Double click [DDJ-SZ2_vxxx.app] to open the file.

<STEP2> Select a language.

Select the language you want to use and click "OK".




- ✓ Please refer to "Tips: When [Your DDJ-SZ2 is not connected] is shown during updating the firmware" in a later section if the same message is popped up after clicking "OK".

<STEP3> Check the firmware version.

Ensuring that the version is x.xx. Click "Start".


Do not disconnect the power cable and the USB cable during the update.

Please use an **AC adaptor** to power your laptop during update.



<STEP4> The updating starts.


Please wait until the progress bar reaches to the right end.



<STEP5> Complete the update process.

When the message below is displayed, click "OK".

When all the LEDs of the MASTER level meter on DDJ-SZ2 are lit, the firmware update is completed.



<STEP6> Reboot the DDJ-SZ2.

Turn off the power of the DDJ-SZ2 and then turn it on again.


E. Check the firmware version

Check the firmware version of the DDJ-SZ2 as described in [A. Check the current Firmware Version of DDJ-SZ2].

When you find the version you wanted in the Settings Utility, the firmware update is successfully complete.

Tips: When [Your DDJ-SZ2 is not recognized] is shown during updating the firmware

When the following message appears after selecting a language, check the following tips.




- Is the USB cable connected to a USB-A terminal?
If it is not connected, connect the cable to a USB-A port and start the updating steps from the beginning again.

- When the above message appears even if the cable is connected to a USB-A port, please follow the steps below.
 - 1) Uninstall the driver software of DDJ-SZ2.
How to uninstall the driver software:
 - ✓ For Mac users:
Double click the driver software and then double click [DDJ-SZ2 Uninstaller.app].
Follow the instructions in your computer after this.
 - ✓ For Windows users:
Navigate to [Start] menu > [Control panel] -> [Programs].
Then select "Pioneer DDJ -SZ2 Driver" and click "Uninstall".The latest driver software is available from the following link.
<http://pioneerdj.com/support/index.php?lang=en>
 - 2) Update the firmware again from the beginning.
 - 3) After completing the firmware update, install the driver software again.
Please see the Operating Instructions to learn how to install the driver software.

Tips: How to cope with abnormal termination:

If you fail to update the firmware and the following message appears, turn off the power of DDJ-SZ2 and turn it on again. Then start from the beginning of the above Updating Procedures.



[Reference information]

This updater has been verified to operate on the operating systems below

Windows:	Windows 10 / Windows 8.1 / Windows 7
Mac:	macOS 10.12 / OS X 10.11 / OS X 10.10

Approximately 2 minutes is required for updating.

The images shown in this Guide may not be the same as the current ones.

About Trademarks and Registered Trademarks

- “Pioneer DJ” is a trademark of PIONEER CORPORATION, and is used under license.
- Microsoft and Windows are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries.
- macOS, OS X and Finder are trademarks of Apple Inc., registered in the U.S. and other countries.
- Other stated company names, product names, technology names, etc. are the trademarks or registered trademarks of their respective owners.

©2017 Pioneer DJ Corporation. All rights reserved.

PIONEER DJ CORPORATION

6F, Yokohama i-Mark Place, 4-4-5 Minatomirai, Nishi-ku, Yokohama, Kanagawa 220-0012 Japan