

*Pioneer*

DJ MIXER

**DJM-350**

Firmware Update Guide

## How to check the version

**STEP 3.**  
Level meterLED show the version.

< ex. Version 1.04 >

(1) (0) (4) (Blank)

(repeat)

**STEP 4.**  
Stand by the power  
Complete version check

**STEP 1.**  
Turn off the power of this unit.

**STEP 2.**  
Hold "CRUSH" & "FILTER".  
After that, press "POWER" buttons.

## How to update

**STEP 1.**  
Write the firmware into the root of USB-Memory.

Update file

**STEP 5.**  
**Start uploading**  
Blinking the top light of CH2 LEVEL METER, shows update mode start working. Uploading completed when all of light is lighting up. (The update will be completed in approx. 1minute)  
\*Do not turn the power off during the update

**STEP 6.**  
**Stand by the power**  
Stand by the power by pressing "Power" buttons 2more seconds. Then remove the USB memory.

**STEP 7.**  
Check the version is updated.

**STEP 3.**  
Turn off the power of this unit, and Put the USB-Memory into the unit.

**STEP 2.**  
**Stand by the power**  
Stand by the power by pressing "POWER" buttons 2more seconds.

**STEP 4.**  
**Update mode start**  
Turn on the power of your CDJ player during press both "FADER START" buttons

## *About trademarks and registered trademarks*

- Pioneer is a registered trademark of PIONEER CORPORATION.

© 2012 PIONEER CORPORATION. All rights reserved

---

*PIONEER CORPORATION*

1-1, Shin-ogura, Saiwai-ku, Kawasaki-shi, Kanagawa 212-0031, Japan