

Pioneer

DJ SYSTEM

XDJ-R1



Firmware Update Guide

Before start

Please download the firmware from the Pioneer Support site and prepare a USB memory stick to be used for updating. Be sure to use it for updating the firmware of XDJ-R1.

- Internet connection is required to download the firmware. Be sure to log in with the computer administrator's account to install the firmware of XDJ-R1.
- It is recommend to create a backup of the disc's hot cue information stored in the unit before updating the firmware. Select **[BACK UP]>[SAVE]** from the **[UTILITY]** screen. Please see *Changing the settings* in [Operating Instructions] of XDJ-R1 for detail.
- Downgrading to older versions of firmware is not available.

* If you have any questions, please contact the Pioneer Customer Support Center.

Checking the firmware version


1. Press the [INFO (UTILITY)] button longer than 1 second.

— The [UTILITY] view is displayed on the screen of XDJ-R1.

2. Turn the rotary selector to scroll the screen and display [VERSION No.].

— Press the rotary selector to check the firmware version.

- Press [INFO(UTILITY)] button to close the [UTILITY] view.



Preparing for the update

1. Access the following URL.

<http://pioneerdj.com/support/>

2. Select [Player/DJ system] > [XDJ-R1] > [Software download] > [Firmware].

3. Follow the instruction to download the firmware to your computer.

4. Unzip the downloaded file.

— The file named [xdj_xxxx.bin] is unzipped (xxxx are numerical characters).

Note: Be sure to remain the file name as it is. If the same file is downloaded to the same folder twice, the file name of the second download could be changed.

5. Insert a USB stick to copy the unzipped file to the root directory of the USB device.

— Please use a USB (Mass Storage Class) memory stick formatted in FAT or FAT32.

Note: Ensure that only one update file is saved in a USB memory device when you update the firmware.


Updating the firmware

Note 1: Press the [STANDBY/ON] button to turn the power off and disconnect all the devices and cables except the power cable from the unit.

Note 2: Please make sure to remove all the CDs and other USB devices, if any, from the unit before starting the update.

1. Turn on the power of XDJ-R1 while pressing the [SHIFT] and [USB] buttons on the left deck.

— The message [DOWNLOAD] is displayed on the screen of the unit.



2. Insert the USB stick.

— Insert the USB memory stick, where the update file is copied, into the USB terminal.

3. Start the update

— Both the current version and the updating version are displayed on the screen of XDJ-R1.

— The progress bar appears to show the updating process.



Note: Ensure the USB stick is securely inserted and leave the power of XDJ-R1 on during updating.

4. Complete the update

— The update process is completed in approximately 6 minutes and the message [COMPLETE] is displayed on the screen.

5. Turn off the power of XDJ-R1 and remove the USB stick.

Now, the update is successfully completed.

6. Check the version after finishing the update.

— Turn on the power of XDJ-R1 and check that the firmware is correctly updated by following the instruction in the above described [Checking the firmware version].

If the update does not start or does not finish even after 10 minutes, the downloaded file might be corrupt. Please start again from the above described [Preparing for the update]. Nevertheless, if the update process cannot be completed, the USB device could be the cause of the error. Try to replace the USB stick with another one.

When the error message (E-7024) is displayed on the screen of XDJ-R1 when the power of the unit is turned on after updating the firmware, please start again from the first step of [Updating the firmware].

Nevertheless, if you cannot update the firmware, please contact the Customer Support Center.

About trademarks and registered trademarks

• Pioneer is a registered trademark of PIONEER CORPORATION
The names of companies and products mentioned herein are the trademarks of their respective owners.

© 2013 PIONEER CORPORATION.

All rights reserved.

PIONEER CORPORATION

1-1, Shin-ogura, Saiwai-ku, Kawasaki-shi, Kanagawa 212-0031, Japan